

HCP-204 FIRE ALARM CONTROL PANEL



STANDARD FEATURES

- 4 Class B (Style B) initiating circuits which may be configured as 2 Class A (Style D) circuits
- 2 Class A/B (Style Z/Y) indicating circuits with individual trouble indicators (1.25 Amps max. per circuit)
- Each indicating circuit can be configured as silenceable or non-silenceable. Audibles may be configured as Steady, Temporal Code, California Code or March Time
- Selectable alarm verification on initiating circuits
- Output for 4-wire resettable regulated smoke power supply of 24 VDC 100mA maximum
- Output for RTI or Remote Annunciators of 24VDC, 300 mA max. unfiltered
- Built-in walk test operation
- Auxiliary relay contacts for common alarm, common trouble and common supervisory. If no supervisory circuits are enabled, the supervisory relay becomes a second alarm relay
- 2.75 Amp power supply
- Easy configuration via DIP switches

SPECIFICATIONS	
Primary Input Power	120 volts, 60 Hz, 1 Amps (Optional 220VAC)
Indicating Current	24VDC unfiltered, 2.5Amps
Standby Power	24VDC standby batteries
Charging Capability	4 – 6.5 AH batteries
Dimensions	12 3/4"H x 13 3/4"W x 3 1/8"D

Specifications subject to change without notice.

DESCRIPTION

Hochiki's HCP-204 Fire Alarm Control Panel is a microprocessor based unit designed for small to medium commercial, institutional and industrial occupancies. Fully configurable using DIP switches, it enables the user to configure the system to meet their specific requirements.

The HCP-204 comes standard with 4 Class B (Style B) initiating circuits which may be configured as 2 Class A (Style D) circuits. In addition, it comes equipped with 2 Class A/B (Style Z/Y) indicating circuits which are each rated at 1.25 Amps. The panel also includes a 2.75 amp power supply which powers the system and supplies a 4-wire resettable regulated smoke power supply of 24 VDC 100mA maximum.

The HCP-204 utilizes a simple DIP switch configuration for programming initiating and indicating circuits as well as the enabling and disabling of system functions such as signal silence, fire drill and auxiliary disconnect. Some predefined initiating circuits can optionally be configured as waterflow or latching/non-latching supervisory. In addition the HCP-204 allows for alarm verification on the initiating circuits. The indicating circuits may be configured as silenceable or non-silenceable with the audibles configured for Steady, March-Time, Temporal Code, or California Code. The HCP-204 is equipped with auxiliary relay contacts for common alarm, trouble and supervisory. If no supervisory circuits are enabled, the supervisory relay becomes a second alarm relay.

The cabinet is available in a beige color for the Canadian market and a red exterior for the U.S. and International markets. A Fire Retardant Lexan Window in the hinged door allows for viewing of the status LEDs. It comes with a durable CAT-30 lock and key. Space is provided for up to 10 AH batteries.

PRODUCT LISTINGS



California
State Fire
Marshal
7165-0410:152

Continued on back.

ORDERING INFORMATION

Model	Description
HCP-204	<p>Fire Alarm Control Panel Four Zone Microprocessor Based Fire Alarm Control Panel comes with 4 Class B (Style B) or 2 Class A (Style D) initiating circuits, 2 Class A/B (Style Z/Y) indicating circuits and a 2.75 amp power supply. Allows for one HDACT-100 Digital Communicator or one HPR-100 Polarity Reversal Module or one HRM-204 or HRM-208 Auxiliary Relay Module. Red enclosure comes with keylock door.</p>
HRTI-1	Remote Trouble Indicator
HDACT-100	<p>Adder Modules Digital Alarm Communication Transmitter/Dialer Module</p>
HPR-100	Polarity Reversal/City Tie Module
HRM-204	Auxiliary Relay Module comes with 4 configurable relays
HRM-208	Auxiliary Relay Module comes with 8 configurable relays <i>(Note: Only one of the above modules can be used with the HCP-204)</i>
HRAM-208	<p>Remote Annunciator Remote Multiplex Annunciator comes with common control features, indicators and 8 bi-colored LEDs <i>Controls:</i> Signal Silence, Buzzer Silence, Lamp Test & System Reset <i>Indicators:</i> A.C. On, Common Trouble & Signal Silence</p>